

### Brochure holder system

**Uncut wires**

IS-9310 Wire system **with** 4 meter (157.5") wires

**Pre-cut wires**

IS-9312 Wire system **for Maxi** 2470 mm (97.2") panels


IS-9311 Wire system **for Midi** 2270 mm (89.4") panels

IS-9318 Brochure holders A4 / US letter with 4 connectors


**Please observe:** This system can only be used with a straight Compact or Straight graphic wing module



### Mounting instruction



**1** Push in the small H-profile at the top of the beam and then mount the extra beam in top of that profile.



**2** Mount this assembly at top of the posts.



**3** Attach the graphic panel and adjust the base beam so that its bottom edge aligns exactly with the bottom edge of the graphic.



**4** Hook the top connector of the wire assembly to the top beam.





**5** Mount the first bottom connector.



**6** Screw the bottom fitting of the wire assembly into the connector until the wire is tight. Repeat the process with the top fitting.



**7** Attach the four identical grip connectors to the brochure holder, evenly spaced. Do not overtighten.



**8** Remove the side screws in the grip connectors, position the wire inside the grooves, and reinstall the side screws.



**9** You can now attach more brochure pockets.

### Brochure holder system

#### Uncut wires


IS-9310 Wire system **with** 4 meter (157.5") wires

#### Pre-cut wires

IS-9311 Wire system **for Midi** 2470 mm (97.2") panels

IS-9312 Wire system **for Maxi** 2270 mm (89.4") panels

IS-9318 Brochure holders A4 / US letter  
with 4 connectors



### Cutting wire length

#### Panel height

2270 mm (89.4")

2470 mm (97.2")

4000 mm (157.5")

#### Wire length

2230 mm (87.8")

2430 mm (95.6")

3960 mm (155.9")

#### Only for uncut wires

Adjust the bottom lock bracket and cut the wire to the desired length.

