Frame size: 400 x 230 cm

Lightbox frame

This frame can be used single- or double sided. You always need fabric graphic on both side (printed or unprinted), unless you will use it as a wall mounted frame on a white wall, in which case it's not necessary to use fabric on the reverse side.

Label mark: Top profile End profile **Extension profile Extension profile** Start profile 1000 mm - Item IS-9591 1000 mm - Item IS-9592 1000 mm - Item IS-9590 1000 mm - Item IS-9592 **End profile** 1000 mm - Item IS-9591 **End profile** 1000 mm - Item IS-9591 Label mark: Side 1 (Sade 1A, 1B, 1C) **VERY IMPORTANT!** Before you connect the LED-Extension profile 300 mm - Item IS-Special Extension profile 300 mm - Item IS-Special bar, read how to connect! See reverse side. Start profile 1000 mm - Item IS-9590 Start profile 1000 mm - Item IS-9590 Start profile **Extension profile Extension profile** End profile 1000 mm - Item IS-9590 1000 mm - Item IS-9592 1000 mm - Item IS-9592 1000 mm - Item IS-9591

Label mark: Bottom profile



You must lock all joints with screw brackets in each side.



Corner connection.



Straight connection.

Mount the feet

Item no: IS-9338 (Minimum 2 pcs.)
The frame must be drilled for the feet on the bottom profile.



Mount a foot in each side of the bottom profile.



Mount the LED-bar



■ Attach the bar with twist nuts into the centre slot in the profile.




2 Lock the two screws with the Allen-key.



3 Insert the adaptor cable in the hole in the profile. Each hole fits 2 cables.



Connect the contacts from the LED-bar to the adaptor cable.



Add more LED-bars and connect with that before, approx 10 mm from the first one.



6 Hide the cable in the side slot and secure it with a tape .

Connect the LED-bar and transformer

Connection 400 x 230 cm

Consists of : 4 pcs. Transformer 8 pcs. Adaptor cable 32 pcs. LED bars





Mark Bric Display Corp.

North America Tel. 800.742.6275 Fax 800.565.9506 E-mail: markbric@markbric.com